

## Wi-Fi and Bluetooth Modules

Mod 1	Function	MCU Pin	Pin Name	Function Name	Voltage
2	BLE_RX	U3C(119)	PD5	USART2_TX	+3.3 V
3	BLE_TX	U3C(122)	PD6	USART2_RX	+3.3 V
4	BLE_CTS_N	U3C(118)	PD4	USART2_RTS	+3.3 V
5	BLE_RTS_N	U3C(117)	PD3	USART2_CTS	+3.3 V
14	BLE_REG_ON	U3C(44)	PC4	-	+3.3 V
20	WIFI_SDIO_CLK	U3C(113)	PC12	-	+3.3 V
22	WIFI_SDIO_CMD	U3C(116)	PD2	-	+3.3 V
23	WIFI_SDIO_D2	U3C(111)	PC10	-	+3.3 V
24	WIFI_SDIO_D0	U3C(98)	PC8	-	+3.3 V
25	WIFI_SDIO_D3	U3C(112)	PC11	-	+3.3 V
26	WIFI_SDIO_D1	U3C(99)	PC9	-	+3.3 V
27	WIFI_HOST_WAKE	U3C(97)	PC7	-	+3.3 V
28	WIFI_REG_ON	U3B(135)	PB5	-	+3.3 V
37	SLEEP_CLK	U3B(100)	PA8	-	+3.3 V
38	BLE_HOST_WAKE	U3C(45)	PC5	-	+3.3 V
39	BLE_DEV_WAKE	U3C(96)	PC6	-	+3.3 V

## Temperature Sensor

Function	MCU Pin	Pin Name	Function Name	Voltage
TEMP_ADC	U3D(22)	PF10	ADC3_IN8	+3.3 V

## Serial Flash 16 Mbit

U2	MCU Pin	Pin Name	Function Name	Voltage
1	SPI1_NSS	U3B(40)	PA4	+3.3 V
2	SPI1_MISO	U3B(42)	PA6	+3.3 V
3	+3.3 V	-	-	-
4	GND	-	-	-
5	SPI1_MOSI	U3B(43)	PA7	+3.3 V
6	SPI1_SCK	U3B(41)	PA5	+3.3 V
7	+3.3 V	-	-	-
8	+3.3 V	-	-	-

## Disclaimer of Warranty

All materials, information and services are provided "as-is" and "as-available" for your use. Future Electronics disclaims all warranties of any kind, either express or implied, including but not limited to, the implied warranties of merchantability and fitness for a particular purpose, title or non-infringement. You acknowledge and agree that the reference designs and other such design materials included herein are provided as an example only and that you will exercise your own independent analysis and judgment in your use of these materials. Future Electronics assumes no liability for your use of these materials for your product designs.

## Indemnification

You agree to indemnify, defend and hold Future Electronics and all of its agents, directors, employees, information providers, licensors and licensees, and affiliated companies (collectively, "Indemnified Parties"), harmless from and against any and all liability and costs (including, without limitation, attorneys' fees and costs), incurred by the Indemnified Parties in connection with any claim arising out of any breach by You of these Terms and Conditions of Use or any representations or warranties made by You herein. You will cooperate as fully as reasonably required in Future Electronics' defense of any claim. Future Electronics reserves the right, at its own expense, to assume the exclusive defense and control of any matter otherwise subject to indemnification by You and You shall not in any event settle any matter without the written consent of Future Electronics.

## Limitation of Liability

Under no circumstances shall Future Electronics, nor its agents, directors, employees, information providers, licensors and licensees, and affiliated companies be liable for any damages, including without limitation, direct, indirect, incidental, special, punitive, consequential, or other damages (including without limitation lost profits, lost revenues, or similar economic loss), whether in contract, tort, or otherwise, arising out of the use or inability to use the materials provided as a reference design, even if we are advised of the possibility thereof, nor for any claim by a third party.



# NEBULA REV 2.0 IoT DEVELOPMENT KIT QUICK START GUIDE

## Product Overview

The Nebula board is an IoT cloud ready board which allows developers to quickly prototype and deploy their IoT ecosystems.

Wireless connectivity is supported by the Murata 1DX module which is powered by the Cypress CYW4343W Wi-Fi (802.11 b/g/n) and Bluetooth Smart Ready (V4.2 +EDR) chipset radio. The module is designed to fit into small spaces and is smaller than a dime. The Nebula is driven by the STM32F429 ARM Cortex-M4 Microcontroller and includes 16 Mb of serial flash.

The Nebula board supports application development through Cypress' WICED (Wireless Internet Connectivity for Embedded Devices) platform. WICED is the only SDK that combines wireless, MCUs and memory in one


environment that runs on Windows, OS X and Linux through Eclipse-based IDE.

Equipped to support 4 different interfaces to access the STM32F429 peripherals, the Nebula board enables developers to create any IoT application:

1. **Arduino™ Compatible Shield**
2. **mikroBUS™ Socket**
3. **Pmod™ Type 2A**
4. **USB Device**

The Nebula board has been designed for novices and expert developers alike looking to explore the vast opportunities in IoT applications such as asset tracking, energy management, fitness, lighting controls, HVAC, portable controls, security and building automation.

## Board Components



Documentation and tools are available for download at

<https://community.cypress.com/community/partners/future-connectivity-solutions>



mikroBUS Adapters				
J4	Function	MCU Pin	Pin Name	Voltage
1	MIKRO_AD	U3B (37)	PA3	+3.3 V
2	MIKRO_RST	U3D (12)	PF2	+3.3 V
3	MIKRO_CS	U3D (3)	PE4	+3.3 V
4	MIKRO_SCK	U3D(1)	PE2	+3.3 V
5	MIKRO_MISO	U3D(4)	PE5	+3.3 V
6	MIKRO_MOSI	U3D(5)	PE6	+3.3 V
7	+3.3 V	-	-	-
8	GND	-	-	-

mikroBUS Adapters				
J6	Function	MCU Pin	Pin Name	Voltage
9	GND	-	-	-
10	+5 V	-	-	+5 V
11	MIKRO_SDA	U3D(10)	PF0	+3.3 V
12	MIKRO_SCL	U3D(11)	PF1	+3.3 V
13	MIKRO_TX	U3D(58)	PE7	+3.3 V
14	MIKRO_RX	U3D(59)	PE8	+3.3 V
15	MIKRO_INT	U3C(27)	PC1	+3.3 V
16	MIKRO_PWM	U3B(36)	PA2	+3.3 V

Arduino Connectors				
J8	Function	MCU Pin	Pin Name	Voltage
1	NC	-	-	-
2	GND	-	-	-
3	GND	-	-	-
4	+5 V	-	-	-
5	+3.3 V	-	-	+5 V
6	ARD_RESET	U3C (123)	PD7	-
7	+3.3 V	-	-	-
8	NC	-	-	-

Arduino Connectors				
J3	Function	MCU Pin	Pin Name	Voltage
1	ARD_I00	U3C(78)	PD9	+3.3 V
2	ARD_I01	U3C(77)	PD8	+3.3 V
3	ARD_I02	U3C(80)	PD11	+3.3 V
4	ARD_I03	U3C(81)	PD12	+3.3 V
5	ARD_I04	U3D(63)	PE10	+3.3 V
6	ARD_I05	U3D(65)	PE12	+3.3 V
7	ARD_I06	U3D(66)	PE13	+3.3 V
8	ARD_I07	U3D(67)	PE14	+3.3 V

Arduino Connectors				
J9	Function	MCU Pin	Pin Name	Voltage
1	AD_CH0	U3D (13)	PF3	+3.3 V
2	AD_CH1	U3D (14)	PF4	+3.3 V
3	AD_CH2	U3D (15)	PF5	+3.3 V
4	AD_CH3	U3D (19)	PF7	+3.3 V
5	AD_CH4	U3D (20)	PF8	+3.3 V
6	AD_CH5	U3D (21)	PF9	+3.3 V

Arduino Connectors				
J2	Function	MCU Pin	Pin Name	Voltage
1	ARD_I08	U3D(142)	PE1	+3.3 V
2	ARD_I09	U3D(141)	PE0	+3.3 V
3	ARD_I010	U3B(73)	PB12	+3.3 V
4	ARD_I011	U3C(29)	PC3	+3.3 V
5	ARD_I012	U3C(28)	PC2	+3.3 V
6	ARD_I013	U3B(74)	PB13	+3.3 V
7	GND	-	-	-
8	ARD_AVREF	-	+3.3 V	-
9	ARD_SDA	U3B(137)	PB7	+3.3 V
10	ARD_SCL	U3B(136)	PB6	+3.3 V

Pmod Connectors				
J1	Function	MCU Pin	Pin Name	Voltage
1	PMOD_D0	U3E(93)	PG8	+3.3 V
2	PMOD_D1	U3E(129)	PG14	+3.3 V
3	PMOD_D2	U3E(127)	PG12	+3.3 V
4	PMOD_D3	U3E(128)	PG13	+3.3 V
5	GND	-	-	-
6	+3.3 V	-	-	-
7	PMOD_D4	U3B(34)	PA0	+3.3 V
8	PMOD_D5	U3B(35)	PA1	+3.3 V
9	PMOD_D6	U3C(114)	PD0	+3.3 V
10	PMOD_D7	U3C(115)	PD1	+3.3 V
11	GND	-	-	-
12	+3.3 V	-	-	-

LED and User Buttons			
Function	MCU Pin	Pin Name	LEVEL
LED1_GREEN	U3B(47)	PB1	Active High
LED1_RED	U3B(46)	PB0	Active High
LED2_GREEN	U3D(49)	PF11	Active High
LED2_RED	U3B(48)	PB2	Active High
USER_BUTTON1	U3E(91)	PG6	Active High
USER_BUTTON2	U3E(89)	PG4	Active High