


Squba 1.8

INTERCONNECT SYSTEMS



REVISION:

ECR/ECN INFORMATION:

A1

EC No: 172921

DATE: 2018 / 2 / 28

TITLE:

APPLICATION SPECIFICATION Squba 1.8 Interconnect System

SHEET No.

1 of **12**

DOCUMENT NUMBER:

2042200000-AS

CREATED / REVISED BY:
TGREGORI

CHECKED BY:
RHODGE

APPROVED BY: RHODGE



1.0 **SCOPE**

This Application Specification covers the application and end-usage requirements for the Squba 1.8 Sealed Wire-To-Wire, 1.80mm pitch single row connector series which uses copper terminals with tin plated contact interface terminated with 22 to 24 AWG wire using Molex crimp technology. The mated system meets IP67 requirements.

2.0 PRODUCT DESCRIPTION

2.1 NAMES AND SERIES NUMBER(S)

Description	Series Number
Squba 1.8, Receptacle Assembly	204220
Squba 1.8, Plug Assembly	204223
Squba 1.8, Receptacle Crimp Terminal	204301
Squba 1.8, Plug Crimp Terminal	204226

2.2 DIMENSIONS, MATERIALS, PLATINGS AND MARKINGS

See the appropriate sales drawings for the information on dimensions, materials, platings and markings.

3.0 APPLICABLE DOCUMENTS AND SPECIFICATIONS

Product Specification	2042200000-PS
Receptacle Assembly sales drawing	2042200000-SD
Plug Assembly sales drawing	2042230000-SD
Receptacle Crimp Terminal sales drawing	2043010000-SD
Plug Crimp Terminal sales drawing	2042260000-SD
Test Summary	2042200000-TS
Receptacle Assembly Packaging Specification	2042200000-PK
Plug Assembly Packaging Specification	2042230000-PK
Receptacle Crimp Terminal Packaging Specification	2042200000-PK
Plug Crimp Terminal Packaging Specification	2042230000-PK
Applicator Tool Crimp Specification	638083700
Hand Tool Crimp Specification	2002180400


REVISION:	ECR/ECN INFORMATION:	TITLE:			SHEET No.
A1	EC No: 172921	APPLICA Sauba 1	2 of 12		
A	DATE: 2018 / 2 / 28	Squba 1.	8 Interconnect Sy	Stem	20112
DOCUMENT	NUMBER:	CREATED / REVISED BY:	CHECKED BY:	APPRO\	/ED BY:
2042200000-AS		TGREGORI	RHODGE	RHO	DGE
TEMPLATE ELLENAME: PRODUCT SPECISIZE AVAILADOC					




4.0 PRODUCT DEFINITION

4.1 CONNECTOR ASSEMBLIES

(4 CKT CONNECTORS SHOWN)






REVISION:	ECR/ECN INFORMATION:	TITLE:		SHEET No.
	EC No: 172921		APPLICATION SPECIFICATION	
A 1	DATE: 2040 / 2 / 20		Squba 1.8 Interconnect System	3 of 12

DATE: 2018 / 2 / 28 **DOCUMENT NUMBER:** CREATED / REVISED BY: CHECKED BY: **APPROVED BY: TGREGORI** 2042200000-AS RHODGE **RHODGE**




4.2 CRIMP TERMINALS




Description	Order Number	Crimp Spec Document Number	
Crimp Applicator	638083700	638083700	
Crimp Hand Tool	2002180400	2002180400	

NOTE: Same crimp applicator and hand tool is used for both Receptacle and Plug crimp terminals

Crimp Applicator







REVISION:	ECR/ECN INFORMATION:	TITLE:		SHEET No.
	EC No: 172921		APPLICATION SPECIFICATION	
∣ A1			Squba 1.8 Interconnect System	4 of 12

Squba 1.8 Interconnect System

DOCUMENT NUMBER:
2042200000-AS

CREATED / REVISED BY:
TGREGORI


RHODGE


TEMPLATE FILENAME: PRODUCT_SPEC[SIZE_A](V.1).DOC



5.0 TERMINAL ORIENTATION DURING INSERTION INTO HOUSING


Terminals are to be inserted in the housings as shown below on sheet 5-8. Notice the orientation of the terminal body relative to the receptacle thumb latch and plug thumb latch hook. Notice the orientation of the terminal body relative to the latch hook. Do not force terminals into the housing cavity. The terminal and housing are designed with silicon seals and other features that will provide some light resistance during insertion as well as retention after insertion but if excessive resistance is felt during insertion pull terminal back out and double check that the terminal orientation per sheets 5-8. Terminals are to be inserted until they are fully seated and audible click is heard. The housing provides a stopping surface and the housing lock finger provides terminal retention and a light audible click to indicate a fully inserted terminal. You can use the PUSH → CLICK → PULL method (sheet 10) during terminal insertion to ensure fully seated terminal.






REVISION:	ECR/ECN INFORMATION: EC No: 172921 DATE: 2018 / 2 / 28		ATION SPECIFICA 8 Interconnect Sy		5 of 12
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	APPRO\	ED BY:
2042200000-AS		TGREGORI	RHODGE	RHO	DGE







REVISION:	ECR/ECN INFORMATION:	TITLE:	SHEET No.
	EC No: 172921	APPLICATION SPECIFICATION	
∣ A1		Squba 1.8 Interconnect System	6 of 12

Squba 1.8 Interconnect System


DOCUMENT NUMBER:
2042200000-AS

CREATED / REVISED BY:
TGREGORI

RHODGE


TEMPLATE FILENAME: PRODUCT_SPEC[SIZE_A](V.1).DOC






A1	EC No: 172921 DATE: 2018 / 2 / 28	APPLICA Squba 1.	7 of 12		
DOCUMENT	NUMBER:	CREATED / REVISED BY:	CHECKED BY:	APPRO\	/ED BY:
2042200000-AS		TGREGORI	RHODGE	RHO	DGE
TEMPLATE FUENAME, PRODUCT SPECIFIZE AVAILANCE					







REVISION: ECR/ECN INFORMATION: TITLE: SHEET No. **APPLICATION SPECIFICATION** EC No: 172921 **A1**

Squba 1.8 Interconnect System 8 of **12**


DOCUMENT NUMBER: CREATED / REVISED BY: CHECKED BY: APPROVED BY: **TGREGORI** 2042200000-AS **RHODGE** RHODGE

DATE: 2018 / 2 / 28



CARE MUST BE TAKEN WHEN HANDLING THE TERMINAL PINS.

DO NOT USE OR TRY TO ATTEMPT TO REWORK BENT OR DAMAGED TERMINAL PINS



REVISION:	ECR/ECN INFORMATION:	TITLE:	SHEET No.
A 4	EC No: 172921	APPLICATION SPECIFICATION	0 . 40
A 1	DATE: 2018 / 2 / 28	Squba 1.8 Interconnect System	9 of 12


 DOCUMENT NUMBER:
 CREATED / REVISED BY:
 CHECKED BY:
 APPROVED BY:

 2042200000-AS
 TGREGORI
 RHODGE
 RHODGE



PUSH → CLICK → PULL

(APPLIES TO BOTH RECEPTACLE AND PLUG)



REVISION:

ECR/ECN INFORMATION:

Α1

EC No: 172921

DATE: 2018 / 2 / 28

TITLE:

APPLICATION SPECIFICATION Squba 1.8 Interconnect System SHEET No.

10 of **12**

DOCUMENT NUMBER:

2042200000-AS

CREATED / REVISED BY: **TGREGORI**


CHECKED BY: **RHODGE**

APPROVED BY: **RHODGE**




6.0 MATING AND UN-MATING

This product contains a polarization feature to ensure proper orientation during mating. This rib feature is shown below. When mated in the improper orientation this rib feature will not allow the product to be mated.



This product also contains a positive locking thumb latch and corresponding latch hook to ensure full mating and prevent accidental un-mating during normal operation. This thumb latch and latch hook features and full mating of the connectors occurs when and after the thumb latch is fully engaged and locked as shown below. A light audible click is heard to indicate fully mated connectors.



REVISION: ECR/ECN INFORMATION:

A1

EC No: 172921

DATE: 2018 / 2 / 28

TITLE:

APPLICATION SPECIFICATION Squba 1.8 Interconnect System

SHEET No.

11 of **12**

DOCUMENT NUMBER:

2042200000-AS

CREATED / REVISED BY:
TGREGORI

CHECKED BY: RHODGE

APPROVED BY:
RHODGE



7.0 PACKAGING

Parts shall be packaged to protect against damage during handling, transit and storage. See packaging specifications listed in section 3.0 (sheet 2).


8.0 OTHER INFORMATION

8.1 CRIMP APPLICATION TOOLING

DEVISION: ECD/ECN INFORMATION: TITLE:

8.2 CABLE TIE AND OR WIRE TWIST LOCATION

CKT Size	Dim T Min.
2-6	50.8 mm (2.00")
8	76.2 mm (3.00")
10	101.6 mm (4.00")



CHEET No

The "T" dimension defines a "free" length of wire, or a length of wire that is not subject to significant bias by external factors such as a wire tie, wire twisting, or other means of bending or deforming of the wires that repositions them from their natural relaxed state or location where they enter the housing. Wires are to be dressed in such a manner to allow the terminals to float freely in the pocket. This dimension is a general recommendation and may need to be adjusted for different wire gauges and wire type and insulation thickness and insulation material.

A1	EC No: 172921 DATE: 2018 / 2 / 28	APPLICA Squba 1.	12 of 12		
DOCUMENT NUMBER:		CREATED / REVISED BY:	CHECKED BY:	APPRO\	/ED BY:
2042200000-AS		TGREGORI	RHODGE	RHO	DGE
	TEMPLATE ELLENAME: PRODUCT, SPECISIZE, ALV. (1)				